



2020.08

EMI2 DUAL SEAL WATER METER

www.eskopacific.com
EMI2 DATASHEET



Ideal for medium seal flush flow rates up to 8.5 GPM.

Monitors both flow rate into the seal and the return (drain) flow out.

APPLICATIONS

- Sealing and cooling water measurement for single and double mechanical seal application

FEATURES

- Solid, reliable construction
- Large selection of flow ranges
- Easy to install and maintain
- Impact resistant flow tube
- Low flow alarm available

EMI2 DUAL SEAL WATER METER

SPECIFICATIONS

MODEL	EMI2-D	EMI2-K	EMI2-S
BODY MATERIAL	DELRIN®	KYNAR®	SS316
Metering tube	Grilamid® TR55 or Polysulphone (PSU)	Grilamid® TR55 or Polysulphone (PSU)	Grilamid® TR55 or Polysulphone (PSU)
Side plate	SS316	SS316	SS316
O-ring seals	Nitrile (optional Viton® or EPDM)	Nitrile (optional Viton® or EPDM)	Nitrile (optional Viton® or EPDM)
Maximum pressure	290 psi	290 psi	440 psi
Maximum temperature			
Grilamid® tube	176°F / 80°C	176°F / 80°C	176°F / 80°C
Polysulphone PSU tube	248°F / 120°C	248°F / 120°C	248°F / 120°C
Connections	1/2" NPT female threads	1/2" NPT female threads	1/2" NPT female threads
Weight	2.1 lb (0.95 kg)	2.1 lb (0.95 kg)	4.4 lb (2.0 kg)

Build options	Body material, metering tube, O-ring seals
Optional accessories	Inductive adjustable alarm, pressure gauge (with optional red set pointer), mounting stand, flow marker for optimal flow rate or range, pair with constant flow regulator Model EFR

EMI2 DUAL SEAL WATER METER

SEAL WATER METER

EMI

SINGLE FLOW TUBE
DUAL FLOW MODEL

2

END BLOCK MATERIAL	Aluminum	A
	Delrin® (POM)	D
	Kynar® (PVDF)	K
	SS316	S

FLOW RANGE	WATER		
	GPM	LPM	
NOTE: Flow range codes have been updated.	0.5	2	J
	0.9	3	K
	1.4	5	L
	2.2	9	M
Please contact us for model code conversion information.	2.6	10	O
	4.25	16	P
	6	22	S
	8.5	32.5	T

SCALE	Water GPM	1
	Water LPM	4
	Relative Scale (1-10)	R

OPTIONS	PES/PSU flow tube	P
	Viton® O-ring seals	V
	EPDM O-ring seals	E
	Backpressure valve	B
	Gauge (160 psi standard)	G
	Mounting bracket	M



BODY MATERIALS



METERING TUBE



PRESSURE GAUGE



ALARM SENSOR